



Via S.Croce n°121 z.i.
47032 Berinoro (FC) Italia

CLICK INSTALLATION INSTRUCTIONS 40001000:

1. Remove the CLICK cover cap (1) by turning it anti-clockwise.
2. Loosen the screws (2).
3. Remove the CLICK upper cover (3) by rotating it anti clock-wise.
4. Insert each single wire into the cable hole (5). Do not remove or tamper with the cable hole (5) so as not to jeopardize the IP rate of the fitting.

CAUTION: The outer diameter of the single electrical wires must be lower than 3 mm and their nominal thickness

5. Connect the conductors to the terminal block (6) by blocking each wire in the relevant compartment (7).
 6. Fix the base of the CLICK to the wall/ceiling (4) by using the screws and expanders (not included in the packaging);
- CAUTION:** use the reference notches on the CLICK (4) to install the models SNAP, SIMPLY in the desired position (see pict.1).

7. Insert the CLICK upper cover (3) by rotating it clockwise until it stops and then tighten the screws (2).
8. You can now either reposition the orange protection cap on the CLICK or directly install one of the CLICK & LIGHT models on it.
9. To cover with the orange cover cap (1), simply place it over the CLICK by matching reference notch A on the cover (1) with the notch B on the CLICK base (4) (see pict. 2) and turn it clockwise until it stops to guarantee the declared IP rate. To install the luminaire follow the use and maintenance instructions.

Use and maintenance instructions

CLICK&LIGHT SYSTEM

Light fitting including the quick connection system CLICK and a luminaire of the CLICK & LIGHT series

TECHNICAL DETAILS: please refer to the product label

The UE declaration of conformity can be downloaded from our website www.marecoluce.it

Insulation class II

IP65 Protection degree against dust ingress, solid particles, moisture

Caution, risk of electrical shock

This product must not be disposed as a normal household waste

WARNINGS:

- THE SAFETY OF THIS PRODUCT IS GUARANTEED ONLY WITH THE RESPECT OF THE EXISTING RULES FOR THE ELECTRICAL SYSTEMS, AND WITH THE APPROPRIATE USE OF THESE INSTALLATION INSTRUCTIONS, THEREFORE IT IS NECESSARY TO KEEP THEM
- THE IMPROPER USE OF THIS PRODUCT IS FORBIDDEN; ANY TAMPERING WITH THE PRODUCT OR MODIFICATION OF THE PRODUCT THAT IS NOT AUTHORIZED BY MARECO LUCE CAN CAUSE DAMAGE TO PEOPLE, ANIMALS OR THINGS, AND WILL VOID ANY WARRANTY OR LIABILITY.
- THE QUICK CONNECTION SYSTEM CLICK MUST BE USED IN COMBINATION WITH ONE OF THE LUMINAIRES OF THE CLICK&LIGHT SERIES (TO BE PURCHASED SEPARATELY)
- SWITCH OFF THE ELECTRICITY BEFORE CONDUCTING ANY KIND OF MAINTENANCE.
- THE PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE BEST PRACTICE,
- IN CASE OF DAMAGED COMPONENTS, PLEASE REPLACE THE FITTING.
- KEEP THE ORANGE COVERING CAP ONCE REMOVED TO INSTALL THE LUMINAIRE ON THE CLICK BASE.
- THE IP65 PROTECTION DEGREE IS VALID WHEN THE CLICK IS INSTALLED AND COVERED BY ITS ORANGE PROTECTION CAP. WITHOUT THE COVER, THE IP RATE OF CLICK IS IP20.

GENERAL MAINTENANCE RECOMMENDATIONS:

- REPOSITION THE ORANGE COVERING CAP ON THE CLICK EACH TIME YOU REMOVE THE LUMINAIRE FROM THE CLICK BASE IN ORDER TO PRESERVE THE IP65 PROTECTION DEGREE. WITHOUT THE ORANGE COVER CAP THE IP PROTECTION DEGREE IS IP20.
- CHECK THE INTEGRITY OF THE COMPONENTS: REPLACE THEM IN CASE OF DAMAGE, REPLACE THE WHOLE FITTINGS.
- CHECK THE INTEGRITY AND THE FLEXIBILITY OF THE GASKETS, WHICH DO NOT HAVE TO HARDEN.
- DO NOT REMOVE OR TAMPER WITH THE CABLE HOLE SO AS NOT TO JEOPARDIZE THE IP RATE OF THE FITTING.
- CHECK THE PLASTIC CASINGS CAREFULLY IN ORDER TO IDENTIFY ANY POSSIBLE INSULATION DAMAGE.

